


注：以下の手順を実行する前に、PC システムで HDD ケースにアクセスできることを確認してください。


更新ソフトウェアは、次の URL からダウンロードしてください。

<https://app.box.com/s/6eyeq431nyej1bx3cig2n94ntwfxjt9o>


1) rar ファイルを解凍し、以下の 2 つのドキュメントを同じファイルに入れます




2) ファイルをクリックして、ASM105xMPTool.exe をダブルクリックして起動する




3) パスワード【asmedia】を入力してください



4) 示すように赤い矢印を確認し、正しいボタンが点灯していることを確認してください



5) IdleTimer でスリープ時間を設定します。



6) 「FW Browser」で「140227_A1_59_01.bin」ファイルを選択して開始します

The screenshot shows the Asmedia 105x MPTool software interface. The title bar reads "Asmedia 105x MPToolVer3, 6, 0, 1 (1.1.0.0)". The interface is divided into several sections:

- Format:** TYPE1, Vendor ID: 174C, Product ID: 55AA, Device Revision: 0100
- Device Configuration:** Serial Number: 0000000000FB. Options include Input From Barcode, Input From HDDSN, S/N CHK HEX, S/N Increase (checked), Hex (checked), and Dec.
- Manufacturer String:** RSH-319
- Product String:** ASM1153e
- Idle Timer:** Never
- Device Function:** USB Status: USB 3.0, MP Auto Mode, Update FW (checked), Reload FW (checked).
- Partition / Format:** Partition Type: MBR, Format Type: FAT32, Drive Label: Test.
- FW Browser:** A file explorer showing the selected file "JA工作\自动休眠\140227_A1_59_01.bin". A red arrow points to this file with the text "1. choose the bin file".
- Preload Browser:** D:\temp
- USB Searching:** A green progress bar at 100%.
- Table:** A table with columns: Port#, Status, VID, PID, Serial Number, FW Version, Capacity, Update, ReLink, Partition, R/W Test, Preload. The table is currently empty.
- Buttons:** A blue play button (start) and a red stop button. A red arrow points to the play button with the text "2. Then click to start".
- Progress Bar:** A progress bar showing 0% completion. Above it are counters for Pass (0), Fail (0), and Total (0).

成功すると【PASS】が表示されます。